

# CAN-UI10

## CANx 10 x Push-button inputs / 1 x PT1000 sensor input, flush-mounted

CAN-UI10 is a flush-mounted 10-channel binary input and LED controller with a built-in temperature sensor and thermostat, transforming any conventional switch into a CANx sensor.

### Physical interfaces

CAN FT	1
Programming / Reset button	1
USB 2.0	1 (only for device firmware upgrade)
Temperature sensor	1
PT1000 input	1
Binary input / LED control	10 (Outputs: 5 V, 5 mA)

### Power

Power supply	24 V DC
Power consumption	0.24 W (stand-by), 0.26 W (max)

### Connections

CAN FT bus / Power	Bus connection terminal, 0.8 mm <sup>2</sup>
I/O ports	2 x 6 pin Sharp ZH 1.5 mm connector (cables included)
PT1000 input	Screw terminals, 0.8 mm <sup>2</sup> .. 1.5 mm <sup>2</sup>

### LED indicators

Green	Bus activity / programming mode
Red	Bus or hardware fault /reset

### Enclosure

Mounting support	Flush-mounted
Dimensions WxHxD	49 x 47 x 19 mm
IP degree of protection	IP20
Net weight	27 g

### Standards compliance

EMC	EN61000-6-1; EN61000-6-3
-----	--------------------------

### Environment

Operational temperature	0 °C .. +45 °C
Storage temperature	-15 °C .. +55 °C
Relative humidity	0% ... 93% (without condensation)

### Warranty

	2 years
--	---------



### Key highlights

#### Robust and efficient communication

Utilizes time-proven CAN FT field bus.

#### High bandwidth CAN FT bus

Supports 48Kbps over CAN FT bus, ensuring fast and reliable data transfer.

#### LoRa-enabled variants

Selected CANx devices offer LoRa 433 wireless communication for flexibility.

#### Seamless protocol interoperability \*

Unified data types enable smooth integration with other systems such as KNX, Modbus, BACnet, MQTT, and more.

#### Co-exists with KNX while enhancing performance \*

Eliminates KNX fieldbus limitations (speed, semantics) while maintaining full user experience and compatibility with KNX.

#### ETS-friendly integration \*

Supports importing KNX project files and enriching them with semantics for advanced data modelling.

#### Comprehensive commissioning \*

Free CANx and DALI web-based commissioning tools available via the LogicMachine app store for device discovery, configuration and diagnostics.

*\* LogicMachine is required for commissioning and interconnectivity with other protocols.*

[logicmachine.net](http://logicmachine.net)