

LogicMachine comparison table

Product code	Product name	Zwave/Bluetooth support through USB	KNX TP1	Ethernet	CAN FT bus	3G/GSM	Power-over-Ethernet	USB	RS-485	RS-485 / RS-232	DALI	1-wire	Built-in KNX Choke	EnOcean 868MHz	Programmable digital I/O	Programmable Analog input or digital output	Binary inputs	Analog inputs	0-10V outputs	4-20mA outputs	Size
LM5Lp2	LogicMachine5 Lite Power with KNX/EIB, ModBus, BACnet, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x			x	1	1	1											3DIN
LM5CLp2	LogicMachine5 Lite Power CANx with CAN FT, ModBus, BacNet, KNXnet/IP, 1 x RS-485, 1 x RS-485/RS-232, PoE	x		x	x		x	1	1	1											3DIN
LM5p2-PMC	LogicMachine5 Power Choke with KNX/EIB, ModBus, BACnet, 1 x RS-485, 1 x USB, 1 x RS-485/RS-232, built-in KNX Choke for powering up to 16 KNX devices, PoE	x	x	x			x	1	1	1			x								4DIN
LM5p2-DW1	LogicMachine5 Power with KNX/EIB, ModBus, BACnet, 1 x RS-485, 1 x RS-485/RS-232, 2 x DALI, 2 x 1-wire optimized for long lines, PoE	x	x	x			x	1	1	1	2	2									4DIN
LM5Cp2-DW1	LogicMachine5 Power CANx with CAN FT, ModBus, BACnet, 1 x RS-485, 1 x RS-485/RS-232, 2 x DALI, 2 x 1-wire optimized for long lines, PoE	x		x	x		x	1	1	1	2	2									4DIN
LM5p2-DR	LogicMachine5 Power with KNX/EIB, ModBus, BACnet, 2 x RS-485, 1 x RS-485/RS-232, 2 x DALI, PoE	x	x	x			x	1	2	1	2										4DIN
LM5Cp2-DR	LogicMachine5 Power CANx with CAN FT, ModBus, BACnet, 2 x RS-485, 1 x RS-485/RS-232, 2 x DALI, PoE	x		x	x		x	1	2	1	2										4DIN
LM5p2-KC	LogicMachine5 Power KNX CANx with CAN FT, KNX TP1, ModBus, BacNet, 2 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x	x		x	1	2	1											4DIN
LM5p2-KCD	LogicMachine5 Power KNX CANx DALI with CAN FT, KNX TP1, DALI ModBus, BacNet, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x	x		x	x	1	1	1										4DIN
LM5p2-RIO2	LogicMachine5 Reactor IO V2 Power with KNX/EIB, ModBus, BACnet, 16 x AI/DO (with pulse meter), 2 x AO, 1 x 1-Wire, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x			x	1	1	1		1				16			2		6DIN
LM5p2-RIO2E	LogicMachine5 Reactor IO V2 EnOcean Power with KNX/EIB, ModBus, BACnet, EnOcean transceiver, 868MHz antenna, 16 x AI/DO (with pulse meter), 2 x AO, 1 x 1-Wire, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x			x	1	1	1		1		x		16			2		6DIN
LM5Cp2-RIO2	LogicMachine5 Reactor IO V2 Power CANx with CAN FT, ModBus, BACnet, KNXnet/IP, 16 x AI/DO (with pulse meter), 2 x AO, 1 x 1-Wire, 1 x RS-485, 1 x RS-485/RS-232, PoE	x		x	x		x	1	1	1		1				16			2		6DIN
LM5p2-RD	LogicMachine5 Reactor Dimmer Power with KNX/EIB, ModBus, BACnet, 2 x DALI, 1 x 1-wire, 8 x AI/DO, 3 x AO 0-0V, 1 x AO 0..20mA, 1 x RS-485, 1 x RS-485/RS-232, PoE, 3x CPU speed	x	x	x			x	1	1	1	2	1				8			3	1	6DIN
LM5p2-RDE	LogicMachine5 Reactor Dimmer EnOcean Power with KNX/EIB, ModBus, BACnet, 2 x DALI, 1 x 1-wire, EnOcean transceiver, 868MHz antenna, 8 x AI/DO, 3 x AO 0-0V, 1 x AO 0..20mA, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x			x	1	1	1	2	1		x		8			3	1	6DIN
LM5Cp2-RD	LogicMachine5 Reactor Dimmer Power CANx with CAN FT, ModBus, BACnet, KNXnet/IP, 2 x DALI, 1 x 1-wire, 8 x AI/DO, 3 x AO 0-10V, 1 x AO 0..20mA, 1 x RS-485, 1 x RS-485/RS-232, PoE	x		x	x		x	1	1	1	2	1				8			3	1	6DIN
LM5Cp2-GSM	LogicMachine5 Reactor GSM CANx with ModBus, BACnet, CAN FT, 3G/GSM, 16 x IO, 1 x AI, 3 x Current clamp inputs, 1 x 1-Wire, 1 x RS-485, 1 x RS-485/RS-232, PoE	x		x		x	x	1	1	1		1				16		4			6DIN
LM5p2-GSM	LogicMachine5 Reactor GSM with KNX/EIB, ModBus, BACnet, 3G/GSM, 16 x IO, 1 x AI, 3 x Current clamp inputs, 1 x 1-Wire, 1 x RS-485, 1 x RS-485/RS-232, PoE	x	x	x	x	x	x	1	1	1		1				16		4			6DIN